

SMP Coaxial Connectors MIL Standard Compliant

SMP Series

Up to 40GHz



■ Features

1. Excellent High Frequency performance
2. Easy push-on lock
3. Wide variations
4. MIL Standard compliant (MIL-STD-348B)
5. RoHS2 compliant
6. Halogen-free

■ Applications

Optical transmission devices,
Data transmission measurement,
Radio communication equipment,
Measuring instruments etc.

■ Functional diagram

Plug side

- Straight plug receptacle
SMP-PR(**)-SMT-1



- Right angle plug receptacle
SMP-LPR(**)-SMT-1



- Conversion adapter (SMP plug to 2.92mm plug)
SMPP(**)-HKP



Jack side

- Jack
SMP-J-SF085



- Right angle jack
SMP-LJ-SF085



- Relay adapter (Jack to Jack)
SMP-A-JJ-645



- Conversion adapter (SMP jack to 2.92mm jack)
SMPJ-HKJ



- Terminator
SMP-TMJ




Product Specifications

| | | | | |
|---------|----------------------------------|------------|-----------------------------|----------------------------------|
| Ratings | Nominal characteristic impedance | 50Ω | Operating Temperature Range | -55°C to +125°C (95% RH or less) |
| | Frequency range | 0 to 40GHz | Storage Temperature Range | -55°C to +50°C (95% RH or less) |

| Items | Specifications | Conditions |
|--|---|---|
| 1. Contact resistance | Center : Not greater than 6mΩ External : Not greater than 6mΩ | Measured at 100mA or below |
| 2. Insulation resistance | Not greater than 1,000MΩ | Measured at 500V DC |
| 3. Withstanding voltage | No flashover or breakdown | 500V AC for 1 minute |
| 4. Voltage standing wave ratio | ● SMP-J-SF085 VSWR : Not greater than 1.3 (0 to 15GHz) VSWR : Not greater than 1.5 (15 to 40GHz) | ● SMP-PR (**)-SMT VSWR : Not greater than 1.5 (0 to 30GHz) |
| 5. Holding power of female contact | Not less than 0.2N | Measured with φ0.35 pin gauge |
| 6. Mating Cycles | Contact resistance at center : Not greater than 12mΩ External : Not greater than 12mΩ No broken, cracked, or loose parts | 500 cycles |
| 7. Moisture resistance of temperature/humidity cycle | Insulation resistance : Not less than 100MΩ (in a high humidity environment) Insulation resistance : Not less than 1,000MΩ (in a dry environment) No broken, cracked or loose parts | Left for 10 cycles (240 hours) in an environment with the temperature ranging from -10 to 65°C and the humidity ranging from 90 to 98%. |
| 8. Temperature cycle | No broken, cracked or loose parts | 5 cycles of the following series of test condition : Temperature : -65°C → - → +125°C → - Time period : 30 min. → 3 min. → 30 min. → 3 min. |
| 9. Salt spray | No considerable corrosion | Continuous 48 hour cycle in 5% salt water solution |

*Measurement of voltage standing wave ratio (VSWR)

The specified values of VSWR noted above, are taken with the test set up shown in the figure below:



Materials / Finish

| Part | Materials | Finish |
|-----------|-----------------|------------------------|
| Shell | Jack | Beryllium copper |
| | Plug | Brass, Stainless steel |
| Contact | Male contact | Phosphor bronze |
| | Female contact | Beryllium copper |
| Insulator | LCP, PTFE resin | ————— |

Product Number Structure

Refer to the below chart of the product number when determining the product specifications.

Please select from the product numbers listed below when placing orders.


SMP - [] - []

① ② ③

| |
|--|
| ① Series name : SMP |
| ② Connector type J : Straight jack LJ : Right angle jack PR : Straight plug receptacle LPR : Right angle plug receptacle A-JJ : Relay adapter |
| ③ Applicable cable SF085 : 0.085-inch coaxial cable SMT : PCB surface mount type 645 : 6.45mm |


*Please contact Hirose for cable assembly specifications.

■ Straight jack (0 to 40GHz)




| Part No. | HRS No. |
|-------------|------------|
| SMP-J-SF085 | 338-1100-0 |

■ Right angle jack (0 to 30GHz)




| Part No. | HRS No. |
|--------------|------------|
| SMP-LJ-SF085 | 338-1101-0 |

■ Straight plug receptacle (0 to 30GHz)



| Part No. | HRS No. |
|------------------|------------|
| SMP-PR(FD)-SMT-1 | 338-1102-0 |
| SMP-PR(LD)-SMT-1 | 338-1103-0 |
| SMP-PR(SB)-SMT-1 | 338-1104-0 |

■ Right angle plug receptacle (0 to 30GHz)




| Part No. | HRS No. |
|-------------------|------------|
| SMP-LPR(FD)-SMT-1 | 338-1105-0 |
| SMP-LPR(LD)-SMT-1 | 338-1107-0 |
| SMP-LPR(SB)-SMT-1 | 338-1108-0 |

Note : Insertion / Extraction Force
 FD : FULL DETENT
 LD : LIMITED DETENT
 SB : SMOOTH BORE

Feb.1.2019 Copyright 2019 HIROSE ELECTRIC CO., LTD. All Rights Reserved.


■ Relay adapter (Jack to Jack) (0 to 40GHz)



| Part No. | HRS No. |
|--------------|------------|
| SMP-A-JJ-645 | 338-1106-0 |


■ Conversion adapter

● SMP jack to 2.92mm jack (0 to 40GHz)



| Part No. | HRS No. |
|----------|------------|
| SMPJ-HKJ | 311-0013-0 |


● SMP plug to 2.92mm plug (0 to 40GHz)



| Part No. | HRS No. |
|--------------|------------|
| SMPP(FD)-HKP | 311-0199-0 |
| SMPP(SB)-HKP | 311-1001-0 |


Note : Insertion / Extraction Force
 FD : FULL DETENT
 LD : LIMITED DETENT
 SB : SMOOTH BORE

●SMA conversion adapter launcher type (SMP jack to SMA jack) (0 to 18GHz)




| Part No. | HRS No. |
|-------------------|------------|
| HRMJ-SMPJ-BPA-18G | 311-0001-0 |

●SMA conversion adapter (SMP jack to SMA jack) (0 to 18GHz)



| Part No. | HRS No. |
|---------------|------------|
| HRMJ-SMPJ-18G | 311-0002-0 |

●SMA conversion adapter (SMP plug to SMA plug) (0 to 18GHz)



| Part No. | HRS No. |
|---------------|------------|
| HRMP-SMPP-18G | 311-0006-0 |

■ Nonreflective terminator
 ■ Product Specifications

| | | | | |
|---------|----------------------------------|------------------|-----------------------------|----------------|
| Ratings | Nominal characteristic impedance | 50Ω | Operating Temperature Range | -40°C to +85°C |
| | Rated frequency | DC to 30GHz | | |
| | Power | 0.25W CW (+65°C) | Operating relative humidity | 95% RH or less |

■ Materials / Finish


| Part | Materials | Finish |
|-------------------|--------------------------------|-------------|
| Shell | Body : Brass | Gold plated |
| | Spring Part : Beryllium copper | |
| Insulator | PTFE | — |
| Female contact | Beryllium copper | Gold plated |
| Resistive element | Metal film | — |

■ Product Number Structure

SMP - TM J


① ② ③

| | |
|------------------|---------------------------|
| ① Series name | SMP |
| ② TM | Non-reflective terminator |
| ③ Connector type | J : Jack type |




| Part No. | HRS No. | Voltage standing wave ratio (V.S.W.R.)(max) | | |
|----------|------------|---|-------------|-------------|
| | | DC to 15GHz | 15 to 25GHz | 25 to 30GHz |
| SMP-TMJ | 353-0024-0 | 1.15 | 1.2 | 1.25 |


◆ Frequency characteristics (TYPICAL)





SMP-J-SF085 with double ended harness




※This data does not include part of micro strip line and 2.92 end launch connector installed on test board by using gating function of vector network analyzer.




SMP-PR(**)-SMT 2.92 End Launch










SMP-LJ-SF085 with double ended harness






※ This data does not include part of micro strip line and 2.92 end launch connector installed on test board by using gating function of vector network analyzer.



◆ Mated dimensions (FD, LD, SB)



| | PLUG | | | | | | JACK | |
|---|--------------|--------------|----------------|--------------|-------------|-------------|------------|-------------|
| | Inches(mm) | | | | | | | |
| | Full detent | | Limited detent | | Smooth bore | | min | max |
| | min | max | min | max | min | max | | |
| A | φ.139(3.53) | φ.145(3.68) | φ.139(3.53) | φ.145(3.68) | φ.139(3.53) | φ.145(3.68) | — | φ.135(3.43) |
| B | φ.124(3.15) | φ.126(3.20) | φ.124(3.15) | φ.126(3.20) | φ.123(3.12) | φ.127(3.23) | .112(2.84) | — |
| C | φ.114(2.90) | φ.118(3.00) | φ.118(3.00) | φ.122(3.10) | — | — | .018(0.46) | .025(0.64) |
| D | .108(2.74) | .112(2.84) | .108(2.74) | .112(2.84) | .108(2.74) | .112(2.84) | .070(1.78) | — |
| E | .051(1.30) | .057(1.45) | .054(1.37) | .060(1.52) | .059(1.50) | .065(1.65) | .008(0.20) | |
| F | .0205(0.521) | .0235(0.597) | .0205(0.521) | .0235(0.597) | — | — | .000(0.00) | |
| G | .033(0.84) | .037(0.94) | .033(0.84) | .037(0.94) | .033(0.84) | .037(0.94) | — | — |
| H | .003(0.08) | .008(0.02) | .003(0.08) | .008(0.02) | .003(0.08) | .008(0.02) | — | — |
| J | .045(1.14) | .055(1.40) | .045(1.14) | .055(1.40) | .045(1.14) | .055(1.40) | — | — |
| K | .014(0.36) | .016(0.41) | .014(0.36) | .016(0.41) | .014(0.36) | .016(0.41) | — | — |

Note : Insertion / Extraction Force

FD : FULL DETENT


LD : LIMITED DETENT

SB : SMOOTH BORE

◆ Connector extraction tools

Extraction tools have been released for jack products of SMP series.

| Part No. | Applicable tool | HRS No. | Reference |
|------------|-----------------|------------|-----------|
| SMP-LJ-*** | SMP-J-N1 | 350-0014-0 | Fig. ① |
| SMP-J-*** | SMP-J-N1 | 350-0014-0 | Fig. ② |
| | SMP-J-N2 | 350-0015-0 | |



Note 1 : The tools can release the lock. After releasing the lock, please hold connector body and pull out.

Note 2 : These extraction tools are designed for SMP series only.

MEMO :

Area with horizontal dashed lines for writing.

Feb.1.2019 Copyright 2019 HIROSE ELECTRIC CO., LTD. All Rights Reserved.

USA:

HIROSE ELECTRIC (U.S.A.), INC. HEADQUARTERS CHICAGO OFFICE
2300 Warrenville Road, Suite 150,
Downers Grove, IL 60515
Phone : +1-630-282-6700
<http://www.hirose.com/us/>

USA:

HIROSE ELECTRIC (U.S.A.), INC. BOSTON OFFICE
300 Brickstone Square Suite 201,
Andover, MA 01810
Phone : +1-978-662-5255

GERMANY:

HIROSE ELECTRIC EUROPE B.V. NUREMBERG OFFICE
Neumeyerstrasse 22-26, 90411 Nurnberg
Phone : +49-911 32 68 89 63
Fax : +49-911 32 68 89 69
<http://www.hirose.com/eu/>

UNITED KINGDOM:

HIROSE ELECTRIC EUROPE BV (UK BRANCH)
4 Newton Court, Kelvin Drive, Knowlhill,
Milton Keynes, MK5 8NH
Phone : +44-1908 202050
Fax : +44-1908 202058
<http://www.hirose.com/eu/>

CHINA:

HIROSE ELECTRIC (CHINA) CO., LTD. SHENZHEN BRANCH
Room 09-13, 19/F, Office Tower Shun Hing Square, Di Wang Commercial Centre,
5002 Shen Nan Dong Road, Shenzhen City, Guangdong Province, 518008
Phone : +86-755-8207-0851
Fax : +86-755-8207-0873
<http://www.hirose.com/cn/>

KOREA:

HIROSE KOREA CO.,LTD.
143, Gongdan 1-daero, Siheung-si,
Gyeonggi-do, 15084, Korea
Phone : +82-31-496-7000
Fax : +82-31-496-7100
<http://www.hirose.co.kr/>

INDIA:

HIROSE ELECTRIC SINGAPORE PTE. LTD. BANGALORE LIAISON OFFICE
Unit No-403, 4th Floor, No-84, Barton Centre, Mahatma
Gandhi (MG) Road, Bangalore 560 001, Karnataka, India
Phone : +91-80-4120 1907
Fax : +91-80-4120 9908
<http://www.hirose.com/sg/>

USA:

HIROSE ELECTRIC (U.S.A.), INC. SAN JOSE OFFICE
2841 Junction Ave, Suite 200
San Jose, CA. 95134
Phone : +1-408-253-9640
Fax : +1-408-253-9641
<http://www.hirose.com/us/>

THE NETHERLANDS:

HIROSE ELECTRIC EUROPE B.V.
Hogehillweg #8 1101 CC Amsterdam Z-0
Phone : +31-20-6557460
Fax : +31-20-6557469
<http://www.hirose.com/eu/>

GERMANY:

HIROSE ELECTRIC EUROPE B.V. HANOVER OFFICE
Bayernstr. 3, Haus C 30855 Langenhagen, Germany
Phone : +49-511 97 82 61 30
Fax : +49-511 97 82 61 35
<http://www.hirose.com/eu/>

CHINA:

HIROSE ELECTRIC (CHINA) CO., LTD. (SHANGHAI, HEADQUARTERS)
18, Enterprise Center Tower 2, 209# Gong He
Road, Jing'an District, Shanghai, CHINA 200070
Phone : +86-21-6391-3355
Fax : +86-21-6391-3335
<http://www.hirose.com/cn/>

HONG KONG:

HIROSE ELECTRIC HONGKONG TRADING CO., LTD.
Room 1001, West Wing, Tsim Sha Tsui Centre, 66
Mody Road, Tsim Sha Tsui East, Kowloon, Hong Kong
Phone : +852-2803-5338
Fax : +852-2591-6560
<http://www.hirose.com/hk/>

SINGAPORE:

HIROSE ELECTRIC SINGAPORE PTE. LTD.
03, Anson Road, #20-01, Springleaf Tower,
Singapore 079909
Phone : +65-6324-6113
Fax : +65-6324-6123
<http://www.hirose.com/sg/>

MALAYSIA:

PENANG REPRESENTATIVE OFFICE
73-3-1, Ideal@The One, Jalan Mahsuri, Bayan
Lepas Penang, 11950, Malaysia
Phone : +604-648-5536
<http://www.hirose.com/sg/>

USA:

HIROSE ELECTRIC (U.S.A.), INC. DETROIT OFFICE (AUTOMOTIVE)
17197 N. Laurel Park Drive, Suite 253,
Livonia, MI 48152
Phone : +1-734-542-9963
Fax : +1-734-542-9964
<http://www.hirose.com/us/>

GERMANY:

HIROSE ELECTRIC EUROPE B.V. GERMAN BRANCH
Schoenbergstr. 20, 73760 ostfildern
Phone : +49-711-456002-1
Fax : +49-711-456002-299
<http://www.hirose.com/eu/>

FRANCE:

HIROSE ELECTRIC EUROPE B.V. PARIS OFFICE
130 Avenue Joseph Kessel, Bat E, 78960
Voisins le Bretonneux, France
Phone : +33-1-85764886
Fax : +33-1-85764823
<http://www.hirose.com/eu/>

CHINA:

HIROSE ELECTRIC (CHINA) CO.,LTD. BEIJING BRANCH
A1001, Ocean International Center, Building 56# East 4th
Ring Middle Road, ChaoYang District, Beijing, 100025
Phone : +86-10-5165-9332
Fax : +86-10-5908-1381
<http://www.hirose.com/cn/>

TAIWAN:

HIROSE ELECTRIC TAIWAN CO., LTD.
103 8F, No.87, Zhengzhou Rd., Taipei
Phone : +886-2-2555-7377
Fax : +886-2-2555-7355
<http://www.hirose.com/tw/>

INDIA:

HIROSE ELECTRIC SINGAPORE PTE. LTD. DELHI LIAISON OFFICE
Office NO.552, Regus-Green Boulevard, Level5, Tower C,
Sec62, Plot B-9A, Block B, Noida, 201301, Uttar Pradesh, India
Phone : +91-12-660-8018
Fax : +91-120-4804949
<http://www.hirose.com/sg/>

THAILAND:

BANGKOK OFFICE (REPRESENTATIVE OFFICE)
Unit 4703, 47th FL., 1 Empire Tower, South Sathorn
Road, Yannawa, Sathorn, Bangkok 10120 Thailand
Phone : +66-2-686-1255
Fax : +66-2-686-3433
<http://www.hirose.com/sg/>

**HIROSE ELECTRIC CO.,LTD.**

2-6-3,Nakagawa Chuoh,Tsuzuki-Ku,Yokohama-Shi 224-8540,JAPAN
TEL: +81-45-620-3526 Fax: +81-45-591-3726
<http://www.hirose.com>
<http://www.hirose-connectors.com>